

WAC LIGHTING

LINE™ & Straight Edge® 120V/24V 60W & 96W Plug-in Class 2 Transformer

Model & Max Output Power	Product	L x W x H
EN-2460-P-AR-S-60	Plug-in Electronic Transformer for Line and Straight Edge 120V Input 24V Output 60 Watt	2.75IN x 1.625IN x 1.75IN
EN-24100-P-AR-S-100	Plug-in Electronic Transformer for Line and Straight Edge 120V Input 24V Output 96 Watt	

Example: **EN-2460-P-AR-S**

DESCRIPTION

Low Voltage plug-in Class 2 electronic transformer designed to be used as a plug-and-play style transformer. Contains an on/off toggle switch at the base and a 72" detachable cord with an open splice. Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits. Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp. Ideal for WAC Lighting under cabinet systems.

FEATURES

- Includes 6' cord and five SL-WC-1 plastic wire clips
- Non-Dimmable
- Built-in auto reset, soft start, short and overload circuit
- 5 year warranty

SPECIFICATIONS

Input:	120 VAC, 50/60Hz
Finish:	White
Standards:	UL, cUL, Dry Location Listed
Construction:	Polycarbonate



FINISHES



White

Fixture Type: _____

Catalog Number: _____

Project: _____

Location: _____