

# WAC LIGHTING

## Solorail™

### 250W Rail Starter Kit

Model	Finish
LM-SK-250E	BN Brushed Nickel

Example: **LM-SK-250E-BN**

#### DESCRIPTION

Designed with the thinnest profile in the industry, the Solorail™ Starter Kit features a low voltage monorail system bendable in the field and can be designed to navigate curves for custom designs. The Solorail™ kit is available in 150W or 250W options, and includes everything you need to build a custom Solorail™ system with your own choice of fixtures or pendants. Accommodates appealing Quick Connect™ pendants or fixtures. Includes 2 X 4ft solorails, 1 X I-Connector, 2 X end caps, 3 X Standoffs for support, and 1 X LM-EN12 transformer.

#### FEATURES

- Use with any combination of pendants or fixtures totaling 250W
- 20 watt minimum load for compatibility with LED lamps and fixtures
- Transformer included
- 5 year warranty

#### SPECIFICATIONS

Input:	120 VAC, 50/60Hz
Dimming:	ELV: % , N/T
Finish:	Electroplated: Brushed Nickel
Operating Temp:	-4°F to 104°F (-20°C to 40°C)
Standards:	UL, cUL, Dry Location Listed

Fixture Type: \_\_\_\_\_

Catalog Number: \_\_\_\_\_

Project: \_\_\_\_\_

Location: \_\_\_\_\_



#### FINISHES:



Brushed  
Nickel